

VIEWING CURRENT RECEIVER SETTINGS

+

GROUP CHANNEL TV
2 3 66

+

SHURE

+

802000

CHANGING RECEIVER SETTINGS

Changing Group/Channel Setting

MENU

+ MENU -

+

SET G/CH

SELECT

GROUP CHANNEL TV
2 3 66

+ or -

GROUP CHANNEL TV
2 4 66

SELECT

GROUP CHANNEL TV
2 4 66

+ or -

GROUP CHANNEL TV
3 4 66

MENU

SAVE ?
+YES -NO

+ or -

Changing Frequency Setting

MENU

+ MENU -

+

SET FREQ

SELECT

784.625

+ or -

785.750

MENU

SAVE ?
+YES -NO

+ or -

Changing Name Setting

MENU

+ MENU -

+

SET NAME

SELECT

SHURE

SELECT

+ or -

UHF NO 1

MENU

SAVE ?
+YES -NO

+ or -

Locking/Unlocking Receiver Settings

MENU

+ MENU -

+

SET LOCK

SELECT

CODE ? _

+ - +
, ,

CODE ? ***

MENU

GROUP CHANNEL TV
2 4 66 A

NOTE: Repeat the above sequence to Unlock the Receiver settings.

Changing Squelch Setting

MENU

+ MENU -

+

SET SQCH

SELECT

MID 00

+ or -

+ 05

MENU


SAVE ?
+YES -NO

+ or -


ACCESSING PROGRAM KEYS

Open battery compartment to access MODE and SET keys.

- U1.** Press tabs on side of U1 to release latch, then flip battery compartment cover open.



- U2.** Unscrew U2 battery compartment cover and slide it down.



CHANGING GROUP SETTING


- 1.** Press and hold MODE key.



- 2.** Press and hold SET key until desired setting is reached.



- 3.** Press MODE key twice to enter new setting.



CHANGING CHANNEL SETTING


- 1.** Press MODE key *twice*.



- 2.** Press and hold SET key until desired setting is reached.



- 3.** Press MODE key again to enter new setting.



LOCKING/UNLOCKING POWER ON


- 1.** Press and hold SET key.



- 2.** Press the MODE key to lock power on.




- 3.** Repeat Steps 1 and 2 to unlock power on function.




LOCKING/UNLOCKING FREQUENCY SETTING

- 1.** Turn transmitter off.



- 2.** Press and hold SET key.

- 3.** Turn transmitter back on while holding SET key. Then release SET key.



- 4.** To unlock frequency setting, repeat Steps 1 – 3.

